

## REDCON R720X MINI DSM2/DSMXReceiver

### Receiver Specifications:

Name: R720X

Modulation: DSM2/DSMX

Band: 2.4GHz

Range: 1000M

Dimensions (W x Lx H): 29x 15x2 mm

Weight: 1.3g

Voltage Range: **3.3V**

Antenna Length Main RX: 15CM, 9CM, 6CM 3 kinds of antenna

Expected Range: 100m (tested with JR DSX9)

### Features

#### **3dbi Antenna, long range**

Preset failsafe system

Quick Connect

Compatibility (Spectrum and JR DSM2 /DSMX): DX6I,DX7,DX8, DSX7,DSX9 DSX11

Working Voltage: 3.3V

Compatible Controllers:

NAZA32

CC3D

KK2

F3

F4

Multiwii-APM

V-BAR-5.3

### Binding Procedure

I. Press bind-button connect power to receiver(you could bind it with REDCON CM703, CM651), please make sure radio in binding process. Receiver LED quick flash then green LED off it means bind is accomplished. Restart the receiver it works and LED keep lit.

II. Please make sure the transmitter in binding process.

III. To set fail-safe throttle and control surface positions, (minimum throttle and all control surfaces set to neutral is suggested). Press and hold the bind button of transmitter (LED will illuminate), Turn on the transmitter.

IV. Receiver LED will change from rapid flashing to slow flashing and a few seconds later when bind is accomplished the LED of receiver will illuminate solid. Failsafe should be programmed correctly .

V. Please use 3.3V power to receiver during binding, DSMX mode is recommended , cause DSMX is new.

**Notes:** Only one time bind procedure is required on a new receiver. Repetitive binding provides no extra security. Always remember to remove the binding harness after successful bind is completed.

**Package including: R720X Receiver \*1 pc**

15CM 天线



9CM 天线



6CM 天线

